

#### Sold & Serviced By: ELECTROMATE Toll Free Phone (877) SERV098 Toll Free Fax (877) SERV099 www.electromate.com sales@electromate.com

#### POWER SUPPLIES

# **PS1050**

Power Supply 10 amps, 50 VDC

## Features

- Input Voltage: 108–264 VAC
- Output Voltage: 50 VDC nominal
- Typical Output Voltage: 56.6V no load 52.8V at 5 amps 48.8V at 10 amps
- Output Current: 10 amps max, continuous
- Input Frequency: 47–63 Hz
- Max Ambient Temp: 55°C
- Filter Capacitor: computer grade (long life)
- Rectifier Bridge: 50 amp, 200 volt
- Output Voltage Ripple: 3% rms max at nominal AC line voltage
- Weight: 19 pounds
- Made in USA

## Description


The PS1050 is a heavy duty linear, unregulated power supply. It is an ideal power source for Applied Motion's 5560, 7080 and 7080i series step motor drives, combining over 500 watts of output power and outstanding reliability.

The PS1050 provides isolation from the AC line and is fused for safety.

The PS1050 is constructed on an open frame aluminum chassis.



# MECHANICAL OUTLINE



# **BLOCK DIAGRAM**

