



Standard
Controllers
Integrated

Rod
Type

Mini

Standard

Controllers
Integrated

PMEC /AMEC PSEP /ASEP ROBO NET PCON ACON PSEL ASEL SSEL


## ■ Configuration: RCP2 — SA7C **56P** Type Encoder Motor

56P: Pulse motor

56 □ size

8: 8mm

4: 4mm



I: Incremental

\* The Simple
absolute encoder
models are
labeled as "I".

\* See page Pre-35 for explanation of each code that makes up the configuration name.

Technical References

(1) When the stroke increases, the maximum speed will drop to prevent the ball screw from reaching the critical rotational speed.

Use the actuator specification table below to check the maximum speed at the stroke you desire.

Since the RCP2 series use a pulse motor, the load capacity decreases at high speeds.

Check in the Speed vs. Load Capacity graph to see if your desired speed and load capacity are supported.

The load capacity is based on operation at an acceleration of 0.3G (0.2G for the 4mm-lead model, or when used vertically) These values are the upper limits for the acceleration.

■ Speed vs. Load Capacity Due to the characteristics of the pulse motor, the RCP2 series' load capacity decreases at high speeds. In the table below, check if your

X : Custom Length SR : Slider Roller R : Robot cable

N : Non P : 1m S : 3m M : 5m

P1:PCON

RPCON

PSEL

P3:PMEC

50: 50mm

800:800mm

(50mm pitch

Option


: Brake (Cable exiting end) : Brake (Cable exiting left)

Brake (Cable exiting right

Reversed-home

BE BL

BR



	Actuator Specifications										
	■ Lead and Load Capacity (Note 1) Please note that the maximum load capacity decreases as the speed increase										
	Madel	Lead	Max. Load Car	Stroke							
	Model	(mm)	Horizontal (kg)	Vertical (kg)	(mm)						
	RCP2-SA7C-I-56P-16-①-②-③-④	16	~ 35	~ 5							
	RCP2-SA7C-I-56P-8-①-②-③-④	8	~ 40	~ 10	(50mm						
	RCP2-SA7C-I-56P-4-1 -2 -3 -4	4	40	∼ <b>1</b> 5	o.omenta)						
Lead and Load Capacity   (Note 1) Please note that the maximum load capacity decreases as the speed increase   Model   Lead (mm)   Max. Load Capacity (Note 1)   Stroke (mm)											

s.	Stroke and Maximum Speed										
		Stroke Lead	$50 \sim 700 \\ \text{(50mm increments)}$	~ 800 (mm)							
		16	533	480							
		8	266	240							
		4	133	120							
	(Unit: mm/s)										

① Stroke Lis	① Stroke List							
Stroke (mm)	Standard Price							
50/100	-							
150/200	-							
250/300	-							
350/400	-							
450/500	-							
550/600	-							
650/700	-							
750/800	_							

③ Cable List								
Туре	Cable Symbol	Standard Price						
	P (1m)	-						
Standard	<b>S</b> (3m)	-						
	M (5m)	-						
	X06 (6m) ~ X10 (10m)	-						
Special Lengths	X11 (11m) ~ X15 (15m)	-						
	X16 (16m) ~ X20 (20m)	-						
	R01 (1m) ~ R03 (3m)	-						
	R04 (4m) ~ R05 (5m)	-						
Robot Cable	R06 (6m) ~ R10 (10m)	-						
	R11 (11m) ~ R15 (15m)	-						
	R16 (16m) ~ R20 (20m)	_						

<sup>\*</sup> See page A-39 for cables for maintenance.

Ball screw ø12mm C10 grade

Option List			
Name	Option Code	See Page	Standard Price
Brake (Cable-exit end)	BE	→ A-25	_
Brake (Cable exiting left)	BL	→ A-25	_
Brake (Cable exiting right)	BR	→ A-25	_
Reversed-home	NM	→ A-33	_
Slider Roller	SR	→ A-36	_


1 Ositioning Hepeatability	10.0211111
Lost Motion	0.1mm or less
Base	Material: Aluminum (special alumite treated)
Allowable Static Moment	Ma: 50.4 N·m Mb: 71.9 N·m Mc: 138.0 N·m
Allowable Dynamic Moment (*)	Ma: 13.9 N·m Mb: 19.9 N·m Mc: 38.3 N·m
Overhang Load Length	Ma direction: 230mm or less; Mb·Mc direction: 230mm or less
Ambient Operating Temp./Humidity	0~40°C, 85% RH or less (Non-condensing)

Directions of Allowable Load Moments

Actuator Specifications

Drive System





Description


RCP2-SA7C




For Special Orders








20, 20, 20 \*3. Reference position for **⊕** ⊕ ⊕ ⊕ ⊕ Cable joint connector \*1 calculating the moment Ma. ₩ 9 9 1 4-M5 depth 10 32±0.02 50 2-ø5H7 depth 10 Ma moment





- \*1.
- The motor-encoder cable is connected here. See page A-39 for details on cables. When homing, the slider moves to the ME; therefore, please watch for any interference with the surrounding \*2.
  - ME: Mechanical end
  - SE: Stroke end
    The values enclosed in "( )" are reference dimensions.

■ Dimensions/Weight by Stroke

Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800
L	353	403	453	503	553	603	653	703	753	803	853	903	953	1003	1053	1103
Α	0	100	100	200	200	300	300	400	400	500	500	600	600	700	700	800
В	0	0	0	1	1	2	2	3	3	4	4	5	5	6	6	7
С	0	0	1	1	2	2	3	3	4	4	5	5	6	6	7	7
D	4	6	6	8	8	10	10	12	12	14	14	16	16	18	18	20
E	2	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3
F	4	4	6	6	8	8	10	10	12	12	14	14	16	16	18	18
Н	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
P	0	85	85	185	185	285	285	385	385	485	485	585	585	685	685	785
Weight (kg)	3.1	3.3	3.6	3.8	4.0	4.2	4.5	4.7	4.9	5.1	5.4	5.6	5.8	6.0	6.3	6.5

## ② Compatible Controllers

Dimensions

The RCP2 series actuators can operate with the controllers below. Select the controller according to your usage.

Name	External View	Model	Description	Max. Positioning Points	Input Voltage	Power Supply Capacity	Standard Price	See Page	
Solenoid Valve Type		PMEC-C-56PI-NP-2-①	Easy-to-use controller, even for beginners		AC100V AC200V	See P481	-	→ P477	
Solelloid valve Type		PSEP-C-56PI-NP-2-0	Operable with same signal as solenoid valve.  Supports both single and double solenoid types.	3 points				-	→ P487
Splash-Proof Solenoid Valve Type	1	PSEP-CW-56PI-NP-2-0	No homing necessary with simple absolute type.				-	→ P407	
Positioner Type	E	PCON-C-56PI-NP-2-0	Positioning is possible for up to 512 points	512 points				-	
Safety-Compliant Positioner Type		PCON-CG-56PI-NP-2-0					-		
Pulse Train Input Type (Differential Line Driver)	ei	PCON-PL-56PI-NP-2-0	Pulse train input type with differential line driver support	(-)	DC24V	2A max.	-	→ P525	
Pulse Train Input Type (Open Collector)		PCON-PO-56PI-NP-2-0	Pulse train input type with open collector support	(-)			-		
Serial Communication Type		PCON-SE-56PI-N-0-0	Dedicated to serial communication	64 points	64 points			-	
Field Network Type		RPCON-56P	Dedicated to field network	768 points			-	→ P503	
Program Control Type	2	PSEL-C-1-56PI-NP-2-0	Programmed operation is possible Can operate up to 2 axes	1500 points			-	→ P557	

\* This is for the single-axis PSEL.

\* ① is a placeholder for the power supply voltage (1: 100V / 2: 100~240V).

IAI

RCP2-SA7C **32** 



PSEP //ASEP ROBO NET ERC2 PCON ACON SCON PSEL ASEL